VIP 3500 POWER JACK OWNER'S INSTRUCTIONS P/Ns 30828, 30900, 31558 (WHITE) and P/Ns 32454, 32455 (BLACK)

H&H Engineering VIP 3,500 Power Jack is designed to lift up to 3,500 pounds a full 18". It's design also includes a night light, attached foot plate, and an emergency crank handle. An important part of owning and using a VIP Jack is being sure it is properly installed and serviced. GENERAL SAFETY

Read and understand the Jack installation instructions. Always block trailer wheel when using the jack. Since there are moving parts inside the jack, be careful of loose clothing, remove or secure loose jewelry (watches, rings, etc.).

jack



Raise your travel trailer's front end and place blocks or stabalizing jacks under the front "A" frame. Lower the trailer until it rests securely on stabilizing jacks or blocks. Retract present jack and remove.

your trailer.


INSTALLATION:

Battle

Phone WWW.


Install Jack in hole and secure with 3 bolts & 3 internal tooth lockwashers (bolt holes are threaded). The 3 bolts should already be on your trailer. The 3 internal lockwashers are supplied by us (in hardware bag). Attach the foot plate to VIP Jack with .50-20 bolt and .50" lockwasher (supplied in hardware bag). IMPORTANT The bolts should 30 amp slow blow fuse To insure a good already be on

electrical ground an



Connect the lead-wire directly to the positive (+) lead of the travel trailer's battery using a twelve (12) gage wire. Be sure the connection is a good one. THE 30 AMP SLO-BLO FUSE MUST BE INSTALLED AS SHOWN.

internal tooth lockwasher must be in place for this bolt. Make sure powdercoat or paint is removed from "A" frame coupler under washer and that tagged hole is used.




IMPORTANT NOTICE:

If it is necessary to change the position of the powerhead relative to the post and flange (in order to provide clearance between powerhead and LP gas bottle or LP gas cover, or more clearance between the lift gate and the powerhead) loosen set screws and rotate head without lifting off coupling. Retighten set screws when head is in desired position.

INITIAL SET-UP AND HOW TO USE YOUR VIP POWER JACK LEVEL:

- 1. Install your VIP Power Jack (SEE INSTALLATION PAGE 1).
- 2. Place a small level inside your RV on a surface you want to level. This might be a counter top or freezer compartment of a refrigerator.
- NOTE: It will be necessary to move this level to check side to side and front to back condition.
- Check the "inside level", level your trailer from side to side with stabilizing jacks or boards under the wheels.
- 4. Checking the "inside level", level your trailer front to back using your VIP Power Jack.
- 5. Carefully adjust the 3 stainless steel screws on the ring that surround the built in bulls-eye level (see picture) until the air bubble is inside the middle circle. Your trailer will then be leveled.



In the future, you can do all your leveling by using your VIP Power

Jack built-in level.

MAINTENANCE:

Once a year, the powerhead should be removed and a liberal amount of grease (preferably a grease with high melting point) applied directly to the coupling on which the drive pin rests.

DO NOT POUR OIL into top of the jack post.

Once a year, the housing cover should be removed and the gears inspected for proper lubrication.

Remove 4 screws and tap around edge of housing to free cover.


DO NOT insert screw driver blade! (This may damage mating surfaces.)

Before replacing cover, clean matging surfaces. If lubrication is needed, use Mobilith 460 grease or equivalent.

Watkins Road / PO Box 460	
e Creek, MI 49016	
ie: 269-965-2371 Fax: 269-965-2389	© Copyright H&H Engineering 1989
.barkermfg.com E-Mail: service@barkermfg.com	m

PAGE:	DATE:	FORM #:
1 of 3	20 DEC 11	30856
REV. LETTER:	ECN#:	APPROVED:
F	14481	

VIP 3500 POWER JACK OWNER'S INSTRUCTIONS P/Ns 30828, 30900, 31558 (WHITE) and P/Ns 32454, 32455 (BLACK)



Datket 1125 Watkins Road / PO Box 460 Battle Creek, MI 49016 Phone: 269-965-2371 Fax: 269-965-2389 www.barkermfg.com E-Mail: service@barkermfg.com

© Copyright H&H Engineering 1989

PAGE:	DATE:	FORM #:
2 of 3	20 DEC 11	30856
REVISION LETTER: F	ECN#: 14481	APPROVED:

VIP 3500 POWER JACK OWNER'S INSTRUCTIONS P/Ns 30828, 30900, 31558 (WHITE) and P/Ns 32454, 32455 (BLACK)

PARTS:	ITEM	PART#	REQ'D	DESCRIPTION
TANIS.	1	30683	1	LOCK INDICATOR LABEL (WHITE)
	1	30341	1	LOCK INDICATOR LABEL (BLACK)
1 😧	2	30331	1	CAP ASS'Y (WHITE)
	2	30330	1	CAP ASS'Y (BLACK)
29	3	619-0003	3	LOCKWASHER INTERNAL TOOTH
4	4	736-2300	1	TOGGLE SWITCH
42	5	736-0008	1	TOGGLE SWITCH
1 5 3 41	6	606-5001	2	SCREW #10 X .50 PHILLIPS HEAD
	7	16392	2	CABLE TIE
9 1 1 1 1 1 1 1 1 1 1	8	617-0009	1	THRUST WASHER
18	9	17419	1	COVER, MACHINED
	9	30774	1	COVER, FINISHED (BLACK)
	10	29306	1	GASKET
	11	28207	1	DRIVE GEAR ASSEMBLY
20	12	28487	1	TORQUE LIMITER
	13	30783	1	BASE FINISHED (WHITE)
	13	30782	1	BASE FINISHED (BLACK)
	14	608-0006	3	SET SCREW .63-18 X .50
S 35	15	618-1002	1	LOCKWASHER .50
	16	27257	1	BLACK WIRE ASS'Y
639	17	17808	1	WIRE CLAMP
33	18	27262	1	LENS
	19	27344	1	MOTOR SLEEVE (WHITE)
	19	27276	1	MOTOR SLEEVE (BLACK)
22	20	26236	1	RUBBER GROMMET
	21	17414	1	ELECTRIC MOTOR
	22	611-2100	2	HEX LOCK NUT
	23	605-0012	4	SCREW
	24	27274	1	MOTOR SEAL
	25	27338	1	COVER WHITE MACHINED
	25	27259	1	COVER BLACK MACHINED
	26	80208	1	WASHER, SPACER
	27	29880	1	CONNECTOR/FUSE HOLDER ASS'Y
	28	623-1216	1	GROOVE PIN
	29	30837	1	COVER LABEL
21	30	606-0010	2	#10-16 X .75 TEK SCREW (ZINC PLATED)
	30	606-0008	2	#10-16 X .75 TEK SCREW (BLACK HEAD)
	31	27313	1	POST ASS'Y -18" BLACK
	31	31367	1	POST ASS'Y- 24" BLACK
	32	600-0011	1	HEX BOLT .50-20 X .75
	33	80501	2	BUSHING
24	34	645-0024	1	FLANGE BUSHING
	35	641-0009	1	BUSHING
	36	603-5016	2	SCREW #10-32 X .75" PHILLIPS
	37	16434	2	HOLE PLUG
	38	621-0004	2	DOWEL Ø.13" X .75 DOWEL
19	39	27253	1	LAMP WIRE ASSEMBLY
	40	30313	1	LENS GASKET
43	41	634-0028	1	RETAINING RING
	42	26097	1	STRAP
	43	21349	1	BASE
	44	28259	1	CRANK HANDLE
	_ //			
	44			
		Ť		

barker

1125 Watkins Road / PO Box 460 Battle Creek, MI 49016 Phone: 269-965-2371 Fax: 269-965-2389 www.barkermfg.com E-Mail: service@barkermfg.com

© Copyright H&H Engineering 1989

PAGE:	DATE:	FORM #:
3 of 3	20 DEC 11	30856
REV. LETTER: G	ECN#: 14471	APPROVED: